

**COS DCE BOOT FSW v1.13 Component Test Results
Requirement 5.1.1.1a Initialize to Boot State After Reset**

Date:	February 13, 2001
Document Number:	COS-03-0038
Revision:	Initial Release
Contract No.:	NAS5-98043
CDRL No.:	N/A

Prepared By: _____ Date _____
Tim Swanson, Software Test Engineer, Design_Net Eng.

Reviewed By: _____ Date _____
K. Brownsberger, COS Sr. Software Scientist, CU/CASA

Reviewed By: _____ Date _____
Grant Blue, COS Software & Operations Manager, BATC

Approved By: _____ Date _____
Barry Welsh, FUV Detector Program Manager. UCB

Approved By: _____ Date _____
John Andrews, COS Experiment Manager, CU/CASA



Center for Astrophysics & Space Astronomy
University of Colorado
Campus Box 593
Boulder, Colorado 80309

REVISIONS

Letter	ECO No.	Description	Check	Approved	Date
-		Initial Release			

Original Release		THE UNIVERSITY OF COLORADO At Boulder The Center for Astrophysics and Space Astronomy			
Name	Date				
Drawn: K. Brownsberger	2-13-01				
Reviewed:		COS DCE BOOT FSW v1.13 Component Test Results Requirement 5.1.1.1a Initialize to Boot State After Reset			
Approved:					
		Size	Code Indent No.	Document No.	Rev
		A		COS-03-0038	-
		Scale: N/A			

Table of Contents

1.	Introduction	2
1.1	Purpose	2
1.2	Scope	2
1.3	Limitations and Constraints	2
1.4	Procedure Overview	2
1.5	Theory of Test	3
2.	Special Instructions	3
2.1	Quality Assurance	3
2.2	Safety	3
2.2.1	Personal Safety	3
2.2.2	Test Article and Equipment Safety	3
2.3	Contamination	4
3.	Support Requirements	4
3.1	Personnel	4
3.2	Tools, Equipment, and Materials	4
3.3	Data/Software	5
3.4	Required Documentation	5
4.	Procedure/Task Steps	5
4.1	Pre-Operation Activities	5
4.1.1	Make Sure that hks Tools Are Active	5
4.1.2	Make Sure that the Proper ROM Is Installed	5
4.1.3	Log In to the EGSE	6
4.1.4	Set Current Directory	6
4.1.5	Slogin as eagcos	6
4.1.6	Set Current Directory	6
4.1.7	Ensure that Proper Files are Present	7
4.2	Operation Execution	7
4.2.1	Establish Initial Test Conditions	7
4.2.2	Execute the Script	7
4.3	Post-Operation Activities	8
4.3.1	Copy Reports to PC Files and Print Them	8
4.3.2	Complete The Test Procedure Form	8

1. INTRODUCTION

1.1 PURPOSE

This document presents the Cosmic Origins Spectrograph (COS) Device Control Electronics (DCE) Flight Software (FSW) certification procedure. The purpose of this procedure is to verify that the FSW satisfies Software Requirements according to the method specified in the DCE FSW Test Plan (STP).

1.2 SCOPE

This test procedure comprises the steps necessary to verify that the FSW satisfies Software Requirements Document (SRD) paragraph 5.1.1.1 — Initialize to Boot State after Reset: Verify that DCE is in Boot State after a Power On Reset (POR).

1.3 LIMITATIONS AND CONSTRAINTS

This test cannot be run in parallel with any other commanding activity directed at the DCE FSW (such as, for example, the periodic transmission of NOOP commands). Test hardware shall be visually inspected, and its configuration noted, prior to conducting this test.

1.4 PROCEDURE OVERVIEW

The procedure requires the `hks` tools running on the Sun SparcStation Electronic Ground Support Equipment (EGSE) whose network IP address is one of

shorty.ssl.berkeley.edu
taiyo.ssl.berkeley.edu
ginger.ssl.berkeley.edu.

Test time shall be scheduled in advance. The Test Conductor must be logged into the Unix system as user `eagcos`, and be commanding from the appropriate directory. This directory contains both the test script file and the shell script file; these two files control test execution. The test is conducted by invoking the shell script. This shell script in turn invokes the Perl 5 program `UniScript.pl`, which resides in its own distinct directory. The test procedure steps have been pre-recorded in the test script file, and are executed interpretively by the `UniScript` program. The shell script and test script are attached to this document as appendices. As `UniScript` executes the test script it sends results to the operator console and to two report files, which are also placed in the current directory. After completion of the test script, the Test Conductor can certify successful test

execution by examining the contents of the report files and determining that required outputs are present in them. Printed copies of the report files are attached to the manually completed checklist (Paragraph 4 below) as documentation of the test.

1.5 THEORY OF TEST

The script sends an `LFDRSTP` command to the DCE and `WAITS` 10 seconds. This command should induce program behavior in the FSW identical that occurring for a Power On Reset. At the end of the wait-period, the HK data are requested and examined. The `LFDOPERT` bit (3) of the `LFSBITS1` word should be 0, indicating that the FSW is operating in Boot State.

2. SPECIAL INSTRUCTIONS

2.1 QUALITY ASSURANCE

QA support is required to verify the configuration and setup environment as well as monitoring test steps and verifying results.

2.2 SAFETY

2.2.1 Personal Safety

To ensure the safety of the test personnel during test execution the guidelines contained in Paragraph 3.4, Reference [1] will be adhered to.

2.2.2 Test Article and Equipment Safety

To ensure the safety and well-being of the COS operations bench, SITS, and related test equipment, the following primary safety requirements will be in effect during the execution of this test procedure:

To ensure the safety and well-being of the COS operations bench, SITS, and related test equipment, the following primary safety requirements will be in effect during the execution of this test procedure:

- If access within one (1) meter of COS bench electronics is necessary, wrist straps attached to technical ground shall be used by all personnel involved in handling of any COS test article. Overcurrent and overvoltage shall be set to remove power if nominal limits are exceeded.

- Emergency Power Shutdown — If, during the COS DCE FSW test, power is ON and a severe test equipment failure results in the power system exceeding specified limits, the Test Conductor shall direct or perform shutdown of power.

2.3 CONTAMINATION

All flight hardware shall be handled with clean latex gloves; it shall be covered with clean ESD material and/or stored in a clean flow-bench.

3. SUPPORT REQUIREMENTS

3.1 PERSONNEL

Execution of the COS DCE FSW certification procedure requires the following personnel (to be completed at the Test Readiness Review (TRR):

Test Director: _____
 Test Conductor: _____
 Test Technician: _____
 QA: _____

3.2 TOOLS, EQUIPMENT, AND MATERIALS

The following is a list of tools, equipment, or materials required in this test. Record manufacturer and model, metrology, or property numbers of equipment used, where appropriate. Record calibration due dates where appropriate.

Boot Mode ROM: schematic **27C256**

Engineering Ground Support Equipment (see paragraph 1.4). Indicate specific configuration:

EGSE			DCE		
taiyo	shorty	Ginger	ETU	DCE #1	DCE #2
X				X	

3.3 DATA/SOFTWARE

The following files must be available present:

Table 3-1: Required Program and Data Files

EGSE (shorty) Directory	File	Description
\disks\galex\users\galex\tcs\uniscrpt\	UniScript.pl	UniScript interpreter
\disks\galex\users\galex\tcs\uniscrpt\stp5_1_1_1a\	U	Shell script for this procedure
Ditto	stp5_1_1_1a.tst	Test script for this procedure (Appendix B)

In addition, the **hks** tools must be active. Directions for activating **hks** are given in UCB-COS-DOC-1118 (Paragraph 3.4, Reference [4]).

3.4 REQUIRED DOCUMENTATION

Reference	Document Number	Title
1	NHB 1700.1(V1-A)	<i>NASA Basic Safety Manual</i>
2	COS-03-0038	<i>DCE FSW Test Procedure 5.1.1.1a</i> (this document)
3	UCB-COS-008	<i>COS FUV Detector Software Test Plan</i>
4	UCB-COS-DOC-1118	<i>COS EGSE Startup Procedure</i>

4. PROCEDURE/TASK STEPS

4.1 PRE-OPERATION ACTIVITIES

4.1.1 Make Sure that **hks** Tools Are Active

Follow the procedure given in Paragraph 3.4, Reference [4].

4.1.2 Make Sure that the Proper ROM Is Installed

The version of the Boot Mode code to be tested is 01.13.

4.1.3 Log In to the EGSE

Step	Operator Entry/System Response	Description
1	C:\tcs\us> telnet shorty.ssl.berkely.edu	Establish connection to shorty via Telnet client program
2	Login: --- Password: xxxxxxxx	Using telnet window, login as user tcs

4.1.4 Set Current Directory

Step	Operator Entry/System Response	Description
3	tcs@shorty% cd ~galex/tcs tcs@shorty% pwd /disks/galex/users/galex/tcs	Change current directory as shown

4.1.5 Slogin as eagcos

Step	Operator Entry/System Response	Description
4	tcs@shorty% slogin -l eagcos shorty.ssl.berkeley.edu eagcos@shorty.ssl.berkeley.edu's password: (<i>get from SSL personnel</i>) Last login: Sat Oct 7 10:41:05 2000 from auntem.ssl.berke Sun Microsystems Inc. SunOS 5.8 Generic February 2000 You have mail. COS EGSE software version: devel	slogin as eagcos ; get password from SSL personnel

4.1.6 Set Current Directory

Step	Operator Entry/System Response	Description
5	eagcos:shorty% cd /disks/galex/users/galex/tcs/uniscript/stp5_1_1_1 eagcos:shorty% pwd /disks/galex/users/galex/tcs/uniscript/stp5_1_1_1a	Change current directory as shown

4.1.7 Ensure that Proper Files are Present

Step	Operator Entry/System Response	Description
6	<pre>Eagcos@shorty% ls -l Total 12 -rw-r--r-- 1 tcs eag 1398 Oct 8 18:03 stp5_1_1_1a.tst -rw-r--r-- 1 tcs eag 62 Oct 9 17:44 u eagcos@shorty% more < u #!/bin/sh perl ../UniScript.pl stp5_1_1_1a "0,0,0,0,0,0,0"</pre>	List files; the .tst file and the shell script u should be present

4.2 OPERATION EXECUTION

4.2.1 Establish Initial Test Conditions

Step	Operator Entry/System Response	Description
7	<pre>Eagcos:shorty% set path=(\$path ~dbb/scripts/bin)</pre>	Set path as shown to enable access to hks tools

4.2.2 Execute the Script

Step	Operator Entry/System Response	Description
8	<pre>sh u \$estring=0,0,0,0,0,0,0 Parameters are: Script File: stp5_1_1_1a #0: 0 #1: 0 #2: 0 #3: 0 #4: 0 #5: 0 #6: 0 #7: 0 Report file >/disks/galex/users/galex/tcs/ver_1_13/stp5_1_1_1a/stp5_1_1_1a.rpl successfully opened.</pre>	Shell to u . You should see the accompanying output as UniScript executes

	<p>Report file</p> <pre>>/disks/galex/users/galex/tcs/ver_1_13/stp5_1_1_1a/stp5_1_1_1a.rp2 successfully opened. Script file /disks/galex/users/galex/tcs/ver_1_13/stp5_1_1_1a/stp5_1_1_1a.tst successfully opened at level 0. "First 10-second wait ..." LFDRSTP "Second 10-second wait ..." WAIT 0: HKV0=1; HKV1=37; wc=10 "Test 5.1.1.1a Succeeded" eagcos:taiyo%</pre>
--	--

4.3 POST-OPERATION ACTIVITIES

4.3.1 Copy Reports to PC Files and Print Them

Using an FTP client, copy the **u**, **stp5_1_1_1a.tst**, **stp5_1_1_1a.rp1**, and **stp5_1_1_1a.rp2** files to appropriate PC files. Include these files as Appendices A, B, C, and D with this completed form.

4.3.2 Complete The Test Procedure Form

Ensure that all blank fields in this report are completed correctly and submit the completed report to QA.

SUMMARY SHEET

OPERATION TITLE: _____ WOA# _____

TEST ARTICLES IDENTIFICATION (including serial and/or part numbers):

TASKS/STEPS COMPLETED: _____

LOCATION: _____

TEST STARTED:	TEST TERMINATED
TIME: _____ Hr/Min	TIME: _____ Hr/Min
DATE: _____	DATE: _____

LOGS USED: _____

ANOMALY REPORTS GENERATED: _____

COMMENTS: _____

TEST CONDUCTOR: _____
Signature/Date

QA REPRESENTATIVE: _____
Signature/Date

Appendix A. Shell Script u

```
#!/bin/sh  
kill cosnoopy  
perl ../UniScript.pl stp5_1_1_1a "0,0,0,0,0,0,0,0"  
cosnoopy&
```

Appendix B. Test Script stp5_1_1_1a.tst

```

; *****
; * DCE FSW Requirement 5.1.1.1a -- Initialize to Boot State after Reset *
; *****
; *****
; * Verify that DCE is in Boot State after a Power On Reset (POR) *
; *****
;
ECHO      2
; *****
; * Wait 10 seconds for any in-progress reset to complete *
; *****
DTG       1,"(1) Verify that DCE is in Boot State after POR"
DTG       1,"(2) First 10-second wait"
WTO       "First 10-second wait ..."
WAIT      10
; *****
; * Use LFDRSTP to create POR *
; *****
DTG       1,"(3) LFDRSTP being sent to create POR"
LFDRSTP
; *****
; * Wait 10 seconds for reset to complete, then read HK, *
; * test bit LFDOPERT (16F4.03) of LFSBITS1 (0="Boot State") *
; *****
DTG       1,"(4) Second 10-second wait ..."
WTO       "Second 10-second wait ..."
WAIT      10,HK
LOG       1,LFSBITS1,LFDOPERT
CHECK     1,((LFSBITS1 & LFDOPERT) == 0)
WTO       "Test 5.1.1.1a Succeeded"

```

Appendix C. Test Report stp5_1_1_1a.rp1

```

                    55555      1      1      1
                    5      11      11      11
aaa      ssss  ttttt  pppp  555      1      1      1
a  a      s      t  p  p      5      1      1      1
aaaaa      sssss  t      pppp      5      1      1      1
a  a      s      t  p      5  5      1      1      1
a  a      ssss      t  p      555  _____  111  _____  111  _____  111

```

```

Ver 01.13  Tue Jan 16 11:43:35 2001  "(1) Verify that DCE is in Boot State after POR"
Ver 01.13  Tue Jan 16 11:43:35 2001  "(2) First 10-second wait"
Ver 01.13  Tue Jan 16 11:43:45 2001  "(3) LFDRSTP being sent to create POR"
LFDRSTP
Ver 01.13  Tue Jan 16 11:43:45 2001  "(4) Second 10-second wait ..."

```

```

Addr Addr HK-Name      Value
-----
16F4-16F5 LFSBITS1      0000

```

```

Addr Mask HK-Bit-Name  Value
-----
16F4 0008 LFDOPERT      0

```

```

CHECK: (($LFSBITS1 & $LFDOPERT) == 0)
eval:  ((0000 & 0008) == 0)

```

S U C C E S S

Appendix D. Test Report stp5_1_1_1a.rp2

				55555		1		1		1	
				5		11		11		11	
aaa		ssss	ttttt	pppp	555	1		1		1	
a a		s	t	p p	5	1		1		1	
aaaaa		sssss	t	pppp	5	1		1		1	
a a		s	t	p	5 5	1		1		1	
a a		ssss	t	p	555	_____	111	_____	111	_____	111

C O M M A N D P A C K E T

	PARM4		PARM3		PARM2		PARM1		PARM0
045AFFFF	04580000	0456FFFF	04540000	0452FFFF	04500000	044EFFFF	044C0000	044AFFFF	04480000
	SN		OPCODE						
0446FFFE	04440001	04420F0F	0440F0F0						
