

**COS DCE BOOT FSW v1.13 Component Test Results  
Requirement 5.1.2.2b Command to Disable/Enable Watchdog**

Date:	February 13, 2001
Document Number:	COS-03-0052
Revision:	Initial Release
Contract No.:	NAS5-98043
CDRL No.:	N/A

Prepared By: \_\_\_\_\_ Date \_\_\_\_\_  
 Tim Swanson, Software Test Engineer, Design\_Net Eng.

Reviewed By: \_\_\_\_\_ Date \_\_\_\_\_  
 K. Brownsberger, COS Sr. Software Scientist, CU/CASA

Reviewed By: \_\_\_\_\_ Date \_\_\_\_\_  
 Grant Blue, COS Software & Operations Manager, BATC

Approved By: \_\_\_\_\_ Date \_\_\_\_\_  
 Barry Welsh, FUV Detector Program Manager. UCB

Approved By: \_\_\_\_\_ Date \_\_\_\_\_  
 John Andrews, COS Experiment Manager, CU/CASA



**Center for Astrophysics & Space Astronomy**  
 University of Colorado  
 Campus Box 593  
 Boulder, Colorado 80309

# REVISIONS

Letter	ECO No.	Description	Check	Approved	Date
-		Initial Release			

Original Release		<b>THE UNIVERSITY OF COLORADO</b> At Boulder <b>The Center for Astrophysics and Space Astronomy</b>												
Name	Date													
Drawn: K. Brownsberger	2-13-01	<b>COS DCE BOOT FSW v1.13 Component Test Results          Requirement 5.1.2.2b Command to Disable/Enable          Watchdog</b>												
Reviewed:		<table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="text-align: center;">Size</td> <td style="text-align: center;">Code Indent No.</td> <td style="text-align: center;">Document No.</td> <td style="text-align: center;">Rev</td> </tr> <tr> <td style="text-align: center;">A</td> <td></td> <td style="text-align: center;">COS-03-0052</td> <td style="text-align: center;">-</td> </tr> <tr> <td>Scale: N/A</td> <td></td> <td></td> <td></td> </tr> </table>	Size	Code Indent No.	Document No.	Rev	A		COS-03-0052	-	Scale: N/A			
Size	Code Indent No.		Document No.	Rev										
A			COS-03-0052	-										
Scale: N/A														
Approved:														

## Table of Contents

1.	Introduction .....	2
1.1	Purpose .....	2
1.2	Scope .....	2
1.3	Limitations and Constraints .....	2
1.4	Procedure Overview .....	2
1.5	Theory of Test .....	3
1.6	Test Script Implementation .....	3
1.6.1	Test Script Arguments .....	3
1.6.2	Test Script Coding .....	3
2.	Special Instructions .....	3
2.1	Quality Assurance .....	3
2.2	Safety .....	3
2.2.1	Personal Safety .....	3
2.2.2	Test Article and Equipment Safety .....	4
2.3	Contamination .....	4
3.	Support Requirements .....	4
3.1	Personnel .....	4
3.2	Tools, Equipment, and Materials .....	4
3.3	Data/Software .....	5
3.4	Required Documentation .....	5
4.	Procedure/Task Steps .....	5
4.1	Pre-Operation Activities .....	5
4.1.1	Make Sure that <b>hks</b> Tools Are Active .....	5
4.1.2	Make Sure that the Proper ROM Is Installed .....	6
4.1.3	Log In to the EGSE .....	6
4.1.4	Set Current Directory .....	6
4.1.5	Slogin as eagcos .....	6
4.1.6	Set Current Directory .....	7
4.1.7	Ensure that Proper Files are Present .....	7
4.2	Operation Execution .....	7
4.2.1	Establish Initial Test Conditions .....	7
4.2.2	Execute the Script .....	7
4.3	Post-Operation Activities .....	9
4.3.1	Copy Reports to PC Files and Print Them .....	9
4.3.2	Complete The Test Procedure Form .....	9

## 1. INTRODUCTION

### 1.1 PURPOSE

This document presents the Cosmic Origins Spectrograph (COS) Device Control Electronics (DCE) Flight Software (FSW) certification procedure. The purpose of this procedure is to verify that the FSW satisfies Software Requirements according to the method specified in the DCE FSW Test Plan (STP).

### 1.2 SCOPE

This test procedure comprises the steps necessary to verify that the FSW satisfies Software Requirements Document (SRD) paragraph 5.1.2.2 — Command to Enable/Disable Watchdog.

### 1.3 LIMITATIONS AND CONSTRAINTS

This test cannot be run in parallel with any other commanding activity directed at the DCE FSW (such as, for example, the periodic transmission of NOOP commands). Test hardware shall be visually inspected, and its configuration noted, prior to conducting this test.

### 1.4 PROCEDURE OVERVIEW

The procedure requires the `hks` tools running on the Sun SparcStation Electronic Ground Support Equipment (EGSE) whose network IP address is one of

**shorty.ssl.berkeley.edu**  
**taiyo.ssl.berkeley.edu**  
**ginger.ssl.berkeley.edu.**

Test time shall be scheduled in advance. The Test Conductor must be logged into the Unix system as user `eagcos`, and be commanding from the appropriate directory. This directory contains both the test script file and the shell script file; these two files control test execution. The test is conducted by invoking the shell script. This shell script in turn invokes the Perl 5 program `UniScript.pl`, which resides in its own distinct directory. The test procedure steps have been pre-recorded in the test script file, and are executed interpretively by the `UniScript` program. The shell script and test script are attached to this document as appendices. As `UniScript` executes the test script it sends results to the operator console and to two report files, which are also placed in the current directory. After completion of the test script, the Test Conductor can certify successful test

execution by examining the contents of the report files and determining that required outputs are present in them. Printed copies of the report files are attached to the manually completed checklist (Paragraph 4 below) as documentation of the test.

## 1.5 THEORY OF TEST

An essential aspect of this test is that the automatic generation by the EGSE software of **LFDNOOPS** be suppressed, since these “feed the dog” — i.e., reset FSW’s countdown to the initiation of a WDR. The script ensures that FSW is in the Boot State by issuing two **POR** packets, followed by one-second **WAITS**. It then issues an **LFDWDOG 1** command to enable watchdog resets and **WAITS** for 11 seconds. The FSW should therefore encounter a WDR after 10 seconds, and this should be reflected in the post-WDR value of the HK variable **LFCTIME**: (much) less than 10. Also, the FSW should generate the diagnostic 001C (Watchdog Reset).

## 1.6 TEST SCRIPT IMPLEMENTATION

### 1.6.1 Test Script Arguments

The script requires no arguments.

### 1.6.2 Test Script Coding

The script uses standard **UniScript** commands and directives.

## 2. SPECIAL INSTRUCTIONS

### 2.1 QUALITY ASSURANCE

QA support is required to verify the configuration and setup environment as well as monitoring test steps and verifying results.

### 2.2 SAFETY

#### 2.2.1 Personal Safety

To ensure the safety of the test personnel during test execution the guidelines contained in Paragraph 3.4, Reference [1] will be adhered to.

2.2.2 Test Article and Equipment Safety

- If access within one (1) meter of COS bench electronics is necessary, wrist straps attached to technical ground shall be used by all personnel involved in handling of any COS test article. Overcurrent and overvoltage shall be set to remove power if nominal limits are exceeded.
- Emergency Power Shutdown — If, during the COS DCE FSW test, power is ON and a severe test equipment failure results in the power system exceeding specified limits, the Test Conductor shall direct or perform shutdown of power.

2.3 CONTAMINATION

All flight hardware shall be handled with clean latex gloves; it shall be covered with clean ESD material and/or stored in a clean flow-bench.

3. SUPPORT REQUIREMENTS

3.1 PERSONNEL

Execution of the COS DCE FSW certification procedure requires the following personnel (to be completed at the Test Readiness Review (TRR)):

Test Director: \_\_\_\_\_

Test Conductor: \_\_\_\_\_

Test Technician: \_\_\_\_\_

QA: \_\_\_\_\_

3.2 TOOLS, EQUIPMENT, AND MATERIALS

The following is a list of tools, equipment, or materials required in this test. Record manufacturer and model, metrology, or property numbers of equipment used, where appropriate. Record calibration due dates where appropriate.

Boot Mode ROM: schematic **27C256**

Engineering Ground Support Equipment (see paragraph 1.4). Indicate specific configuration:

EGSE			DCE		
<b>taiyo</b>	<b>shorty</b>	<b>Ginger</b>	<b>ETU</b>	<b>DCE #1</b>	<b>DCE #2</b>
X				X	

### 3.3 DATA/SOFTWARE

The following files must be present:

**Table 3-1: Required Program and Data Files**

EGSE (shorty) Directory	File	Description
\disks\galex\users\galex\tcs\uniscrpt\	<b>UniScript.pl</b>	<b>UniScript</b> interpreter
\disks\galex\users\galex\tcs\uniscrpt\stp5_1_2_2b\	<b>u</b>	Shell script for this procedure
Ditto	<b>stp5_1_2_2b.tst</b>	Test script for this procedure (Appendix B)

In addition, the **hks** tools must be active. Directions for activating **hks** are given in UCB-COS-DOC-1118 (Paragraph 3.4, Reference [4]).

### 3.4 REQUIRED DOCUMENTATION

Reference	Document Number	Title
1	NHB 1700.1(V1-A)	<i>NASA Basic Safety Manual</i>
2	COS-03-0052	<i>DCE FSW Test Procedure 5.1.2.2b</i> (this document)
3	UCB-COS-008	<i>COS FUV Detector Software Test Plan</i>
4	UCB-COS-DOC-1118	<i>COS EGSE Startup Procedure</i>

## 4. PROCEDURE/TASK STEPS

### 4.1 PRE-OPERATION ACTIVITIES

#### 4.1.1 Make Sure that **hks** Tools Are Active

Follow the procedure given in Paragraph 3.4, Reference [4].

4.1.2 Make Sure that the Proper ROM Is Installed

Visually verify that the ROM under test is installed: if EEPROM, in U18: if PROM, in U2 and U7.

4.1.3 Log In to the EGSE

Step	QA	Operator Entry/System Response	Description
1		C:\tcs\us> <b>telnet shorty.ssl.berkely.edu</b>	Establish connection to shorty via Telnet client program
2		Login: <b>xxx</b> Password: -----	Using telnet window, login as user <b>tcs</b>

4.1.4 Set Current Directory

Step	QA	Operator Entry/System Response	Description
3		tcs@shorty% <b>cd ~galex/tcs</b> tcs@shorty% <b>pwd</b> /disks/galex/users/galex/tcs	Change current directory as shown

4.1.5 Slogin as eagcos

Step	QA	Operator Entry/System Response	Description
4		tcs@shorty% <b>slogin -l eagcos</b> <b>shorty.ssl.berkeley.edu</b> eagcos@shorty.ssl.berkeley.edu's password: ( <i>get from SSL personnel</i> ) Last login: Sat Oct 7 10:41:05 2000 from auntem.ssl.berke Sun Microsystems Inc. SunOS 5.8 Generic February 2000 You have mail. COS EGSE software version: devel	slogin as <b>eagcos</b> ; get password from SSL personnel



4.1.6 Set Current Directory

Step	QA	Operator Entry/System Response	Description
5		eagcos:shorty% <b>cd</b> /disks/galex/users/galex/tcs/uniscript/stp5_1_2_2 <b>b</b> eagcos:shorty% <b>pwd</b> /disks/galex/users/galex/tcs/uniscript/stp5_1_2_2b	Change current directory as shown

4.1.7 Ensure that Proper Files are Present

Step	QA	Operator Entry/System Response	Description
6		eagcos@shorty% <b>ls -l</b> Total 12 -rw-r--r-- 1 tcs eag 1398 Oct 8 18:03 stp5_1_2_2b.tst -rw-r--r-- 1 tcs eag 62 Oct 9 17:44 u	List files; the <b>.tst</b> file and the shell script <b>u</b> should be present

4.2 OPERATION EXECUTION

4.2.1 Establish Initial Test Conditions

Step	QA	Operator Entry/System Response	Description
7		eagcos:shorty% <b>set path=(\$path ~dbb/scripts/bin)</b>	Set path as shown to enable access to hks tools

4.2.2 Execute the Script

Step	QA	Operator Entry/System Response	Description
8		<b>sh u</b>  \$pstring=0,0,0,0,0,0,0 Parameters are: Script File: stp5_1_2_2b #0: 0 #1: 0 #2: 0 #3: 0 #4: 0 #5: 0 #6: 0	Shell to <b>u</b> . You should see the accompanying output as <b>UniScript</b> executes

Step	QA	Operator Entry/System Response	Description
		<pre> #7: 0 Report file  &gt;/disks/galex/users/galex/tcs/ver_1_13/stp5_1_2_2 b/stp5_1_2_2b.rp1 successfully opened. Report file  &gt;/disks/galex/users/galex/tcs/ver_1_13/stp5_1_2_2 b/stp5_1_2_2b.rp2 successfully opened. Script file  /disks/galex/users/galex/tcs/ver_1_13/stp5_1_2_2b/ stp5_1_2_2b.tst successfully opened at level 0.  "Sending two PORs, followed by one-second WAITs" "Sending LFDWDOG 1"  LFDWDOG  ENABLE  "Waiting 11 seconds"  LFDNOOP  WAIT  0: HKV0=2; HKV1=1; wc=5 WAIT  1: HKV1=0; wc=4 WAIT  1: HKV1=2; wc=3 "Test 5.1.2.2b completed successfully" eagcos:taiyo%                     </pre>	

#### 4.3 POST-OPERATION ACTIVITIES

##### 4.3.1 Copy Reports to PC Files and Print Them

Using an FTP client, copy the **u**, **stp5\_1\_2\_2b.tst**, **stp5\_1\_2\_2b.rp1**, and **stp5\_1\_2\_2b.rp2** files to appropriate PC files. Include these files as Appendices A, B, C, and D with this completed form.

##### 4.3.2 Complete The Test Procedure Form

Ensure that all blank fields in this report are completed correctly and submit the completed report to QA.

---

SUMMARY SHEET

OPERATION TITLE: \_\_\_\_\_ WOA# \_\_\_\_\_

TEST ARTICLES IDENTIFICATION (including serial and/or part numbers):

\_\_\_\_\_

TASKS/STEPS COMPLETED: \_\_\_\_\_

\_\_\_\_\_

LOCATION: \_\_\_\_\_

TEST STARTED:

TEST TERMINATED

TIME: \_\_\_\_\_ Hr/Min

TIME: \_\_\_\_\_ Hr/Min

DATE: \_\_\_\_\_

DATE: \_\_\_\_\_

LOGS USED: \_\_\_\_\_

ANOMALY REPORTS GENERATED: \_\_\_\_\_

\_\_\_\_\_

COMMENTS: \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

TEST CONDUCTOR: \_\_\_\_\_

Signature/Date

QA REPRESENTATIVE: \_\_\_\_\_

Signature/Date

## Appendix A. Shell Script u

```
#!/bin/sh  
pkill cosnoopy  
perl ../UniScript.pl stp5_1_2_2b "0,0,0,0,0,0,0,0"  
cosnoopy&
```

---

## Appendix B. Test Script stp5\_1\_2\_2b.tst

```
; *****  
; * DCE FSW Requirement 5.1.2.2b -- Watchdog *  
; * ----- *  
; * Send LFDWDOG 1 *  
; * Verify that with no watchdog service for 10 seconds *  
; * an autonomous WDR does occur *  
; *****  
;  
SYM          ENABLE   =1  
SYM          DIAG001C=0x001C  
SYM          NSEC     =5  
;  
ECHO         2  
;  
DTG          1,"(0) Sending two PORs, followed by one-second WAITS"  
WTO          "Sending two PORs, followed by one-second WAITS"  
;  
POR  
WAIT        1  
POR  
WAIT        1  
;  
DTG          1,"(1) Sending LFDWDOG 1"  
WTO          "Sending LFDWDOG 1"  
;  
LFDWDOG     ENABLE  
;  
DTG          1,"(2) Waiting 11 seconds"  
WTO          "Waiting 11 seconds"  
;  
WAIT        11  
LFDNOOP  
WAIT        NSEC,HK  
LOG          1,LFDOPERT,LFCTIME,LFDDIAGS  
CHECK        1,($LFCTIME < 10)  
DIAG         1,ANY,DIAG001C  
;  
DTG          1,"(3) Test 5.1.2.2b completed successfully"  
WTO          "Test 5.1.2.2b completed successfully"
```

Appendix C. Test Report stp5\_1\_2\_2b.rp1

```

                    55555      1      222      222
                    5      11      2 2      2 2
bbbb      ssss  ttttt  pppp  555      1      2      2
b  b      s      t  p  p  5      1      2      2
bbbb      ssss  t  pppp  5      1      2      2
b  b      s      t  p  5 5      1      2      2
bbbb      ssss  t  p  555  _____ 111  _____ 22222  _____ 22222

```

Ver 01.13 Tue Jan 16 17:10:26 2001 "(0) Sending two PORs, followed by one-second WAITS"

Ver 01.13 Tue Jan 16 17:10:28 2001 "(1) Sending LFDWDOG 1"

LFDWDOG ENABLE

Ver 01.13 Tue Jan 16 17:10:29 2001 "(2) Waiting 11 seconds"

LFDNOOP

```

Addr Mask HK-Bit-Name Value
-----
16F4 0008 LFDOPERT 0

```

```

Addr Addr HK-Name Value
-----
1680-1683 LFCTIME 00000001

```

```

1780-179F LFDDIAGS 011C 0000 0000 0000 0000 0000 0000 0000 0000 0000 0000 0000 0000
0000 0000 0000 0000 0000
17A0-17BF 0000 0000 0000 0000 0000 0000 0000 0000 0000 0000 0000 0000 0000
0000 0000 0000 0000 0000

```

CHECK: (\$LFCTIME < 10)
eval: (0001 < 10)

S U C C E S S

DIAG 1,ANY,DIAG001C
Found: DIAG001C == 28.

S U C C E S S

Ver 01.13 Tue Jan 16 17:10:42 2001 "(3) Test 5.1.2.2b completed successfully"

Appendix D. Test Report stp5\_1\_2\_2b.rp2

```

                    55555          1          222          222
                    5          11          2  2          2  2
bbbb      ssss  ttttt  pppp  555          1          2          2
b  b      s      t  p  p    5          1          2          2
bbbb      ssss  t  pppp    5          1          2          2
b  b      s      t  p    5  5          1          2          2
bbbb      ssss  t  p    555  _____  111  _____  22222  _____  22222

```

-----  
P O R P A C K E T  
-----

80000000  
-----

-----  
P O R P A C K E T  
-----

80000000  
-----

-----  
C O M M A N D P A C K E T  
-----

```

          PARM4          PARM3          PARM2          PARM1          PARM0
045AFFFF 04580000 0456FFFF 04540000 0452FFFF 04500000 044EFFFF 044C0000 044AFFFE 04480001
          SN          OPCODE
0446FFFE 04440001 04420E0E 0440F1F1

```

-----  
C O M M A N D P A C K E T  
-----

```

          PARM4          PARM3          PARM2          PARM1          PARM0
045AFFFF 04580000 0456FFFF 04540000 0452FFFF 04500000 044EFFFF 044C0000 044AFFFE 04480000
          SN          OPCODE
0446FFFD 04440002 04427F7F 04408080

```

-----  
C O M M A N D P A C K E T  
-----

```

          PARM4          PARM3          PARM2          PARM1          PARM0
045AFFFF 04580000 0456FFFF 04540000 0452FFFF 04500000 044EFFFF 044C0000 044AFFFE 04480000
          SN          OPCODE
0446FFFC 04440003 04427F7F 04408080

```

-----  
C O M M A N D P A C K E T  
-----

```

          PARM4          PARM3          PARM2          PARM1          PARM0
045AFFFF 04580000 0456FFFF 04540000 0452FFFF 04500000 044EFFFF 044C0000 044AFFFE 04480000

```



---

	SN		OPCODE
0446FFFB	04440004	04427F7F	04408080

---