

**COS DCE BOOT FSW v1.09 Component Test Results
Requirement 5.2.3.2 Echoes for Command Opcode and Parameters**

Date:	February 13, 2001
Document Number:	COS-03-0026
Revision:	Initial Release
Contract No.:	NAS5-98043
CDRL No.:	N/A

Prepared By: _____ Date _____
 Tim Swanson, Software Test Engineer, Design_Net Eng.

Reviewed By: _____ Date _____
 K. Brownsberger, COS Sr. Software Scientist, CU/CASA

Reviewed By: _____ Date _____
 Grant Blue, COS Software & Operations Manager, BATC

Approved By: _____ Date _____
 Barry Welsh, FUV Detector Program Manager. UCB

Approved By: _____ Date _____
 John Andrews, COS Experiment Manager, CU/CASA



Center for Astrophysics & Space Astronomy
 University of Colorado
 Campus Box 593
 Boulder, Colorado 80309

Table of Contents

1.	Introduction	2
1.1	Purpose	2
1.2	Scope	2
1.3	Limitations and Constraints	2
1.4	Procedure Overview	2
1.5	Theory of Test	3
1.6	Test Script Implementation	3
1.6.1	Test Script Arguments	3
1.6.2	Test Script Coding	3
2.	Special Instructions	3
2.1	Quality Assurance	3
2.2	Safety	3
2.2.1	Personal Safety	3
2.2.2	Test Article and Equipment Safety	3
2.3	Contamination	4
3.	Support Requirements	4
3.1	Personnel	4
3.2	Tools, Equipment, and Materials	4
3.3	Data/Software	5
3.4	Required Documentation	5
4.	Procedure/Task Steps	5
4.1	Pre-Operation Activities	5
4.1.1	Make Sure that hks Tools Are Active	5
4.1.2	Make Sure that the Proper ROM Is Installed	5
4.1.3	Log In to the EGSE	6
4.1.4	Set Current Directory	6
4.1.5	Slogin as eagcos	6
4.1.6	Set Current Directory	6
4.1.7	Ensure that Proper Files are Present	7
4.2	Operation Execution	7
4.2.1	Establish Initial Test Conditions	7
4.2.2	Execute the Script	7
4.3	Post-Operation Activities	8
4.3.1	Copy Reports to PC Files and Print Them	8
4.3.2	Complete The Test Procedure Form	8

1. INTRODUCTION

1.1 PURPOSE

This document presents the Cosmic Origins Spectrograph (COS) Device Control Electronics (DCE) Flight Software (FSW) certification procedure. The purpose of this procedure is to verify that the FSW satisfies Software Requirements according to the method specified in the DCE FSW Test Plan (STP).

1.2 SCOPE

This test procedure comprises the steps necessary to verify that the FSW satisfies Software Requirements Document (SRD) paragraph 5.2.3.2 — Echoes for Command Opcodes and Parameters.

1.3 LIMITATIONS AND CONSTRAINTS

This test cannot be run in parallel with any other commanding activity directed at the DCE FSW (such as, for example, the periodic transmission of NOOP commands). Test hardware shall be visually inspected, and its configuration noted, prior to conducting this test.

1.4 PROCEDURE OVERVIEW

The procedure requires the `hks` tools running on the Sun SparcStation Electronic Ground Support Equipment (EGSE) whose network IP address is one of

shorty.ssl.berkeley.edu
taiyo.ssl.berkeley.edu
ginger.ssl.berkeley.edu.

Test time shall be scheduled in advance. The Test Conductor must be logged into the Unix system as user `eagcos`, and be commanding from the appropriate directory. This directory contains both the test script file and the shell script file; these two files control test execution. The test is conducted by invoking the shell script. This shell script in turn invokes the Perl 5 program `UniScript.pl`, which resides in its own distinct directory. The test procedure steps have been pre-recorded in the test script file, and are executed interpretively by the `UniScript` program. The shell script and test script are attached to this document as appendices. As `UniScript` executes the test script it sends results to the operator console and to two report files, which are also placed in the current directory. After completion of the test script, the Test Conductor can certify successful test

execution by examining the contents of the report files and determining that required outputs are present in them. Printed copies of the report files are attached to the manually completed checklist (Paragraph 4 below) as documentation of the test.

1.5 THEORY OF TEST

The script synthesizes an **LFDNOOP** command whose five parameters, rather than being 0x0000, as in a normal no-op, are, respectively, 0x0010, 0x0020, 0x0030, 0x0040, 0x0050. This syntactically correct (but semantically deviant) command is uplinked to the DCE. The HK data from this command are examined: the image, **LFDCBUF**, is compared, word-by-word, with the contents of Buffer 1, into which the deviant no-op was generated.

1.6 TEST SCRIPT IMPLEMENTATION

1.6.1 Test Script Arguments

The script is not parameterized.

1.6.2 Test Script Coding

The script uses standard **UniScript** commands and directives.

2. SPECIAL INSTRUCTIONS

2.1 QUALITY ASSURANCE

QA support is required to verify the configuration and setup environment as well as monitoring test steps and verifying results.

2.2 SAFETY

2.2.1 Personal Safety

To ensure the safety of the test personnel during test execution the guidelines contained in Paragraph 3.4, Reference [1] will be adhered to.

2.2.2 Test Article and Equipment Safety

- If access within one (1) meter of COS bench electronics is necessary, wrist straps attached to technical ground shall be used by all personnel involved in handling of any COS test article. Overcurrent and overvoltage shall be set to remove power if nominal limits are exceeded.

- Emergency Power Shutdown — If, during the COS DCE FSW test, power is ON and a severe test equipment failure results in the power system exceeding specified limits, the Test Conductor shall direct or perform shutdown of power.

2.3 CONTAMINATION

All flight hardware shall be handled with clean latex gloves; it shall be covered with clean ESD material and/or stored in a clean flow-bench.

3. SUPPORT REQUIREMENTS

3.1 PERSONNEL

Execution of the COS DCE FSW certification procedure requires the following personnel (to be completed at the Test Readiness Review (TRR):

Test Director: _____
 Test Conductor: _____
 Test Technician: _____
 QA: _____

3.2 TOOLS, EQUIPMENT, AND MATERIALS

The following is a list of tools, equipment, or materials required in this test. Record manufacturer and model, metrology, or property numbers of equipment used, where appropriate. Record calibration due dates where appropriate.

Boot Mode ROM: schematic **27C256**

Engineering Ground Support Equipment (see paragraph 1.4). Indicate specific configuration:

EGSE			DCE		
taiyo	shorty	ginger	ETU	DCE #1	DCE #2
	X			X	

3.3 DATA/SOFTWARE

The following files must be present:

Table 3-1: Required Program and Data Files

EGSE (shorty) Directory	File	Description
\disks\galex\users\galex\tcs\uniscrpt\	UniScript.pl	UniScript interpreter
\disks\galex\users\galex\tcs\uniscrpt\stp5_2_3_2\	u	Shell script for this procedure
Ditto	stp5_2_3_2.tst	Test script for this procedure (Appendix B)

In addition, the **hks** tools must be active. Directions for activating **hks** are given in UCB-COS-DOC-1118 (Paragraph 3.4, Reference [4]).

3.4 REQUIRED DOCUMENTATION

Reference	Document Number	Title
1	NHB 1700.1(V1-A)	<i>NASA Basic Safety Manual</i>
2	COS-03-0026	<i>DCE FSW Test Procedure 5.2.3.2 (this document)</i>
3	UCB-COS-008	<i>COS FUV Detector Software Test Plan</i>
4	UCB-COS-DOC-1118	<i>COS EGSE Startup Procedure</i>

4. PROCEDURE/TASK STEPS

4.1 PRE-OPERATION ACTIVITIES

4.1.1 Make Sure that **hks** Tools Are Active

Follow the procedure given in Paragraph 3.4, Reference [4].

4.1.2 Make Sure that the Proper ROM Is Installed

Visually verify that the ROM under test is installed: if EEPROM, in U18: if PROM, in U2 and U7.

Center for Astrophysics & Space Astronomy

4.1.3 Log In to the EGSE

Step	QA	Operator Entry/System Response	Description
1		C:\tcs\us> telnet shorty.ssl.berkeley.edu	Establish connection to shorty via Telnet client program
2		Login: tcs Password:	Using telnet window, login as user tcs

4.1.4 Set Current Directory

Step	QA	Operator Entry/System Response	Description
3		tcs@shorty% cd ~galex/tcs tcs@shorty% pwd /disks/galex/users/galex/tcs	Change current directory as shown

4.1.5 Slogin as eagcos

Step	QA	Operator Entry/System Response	Description
4		tcs@shorty% slogin -l eagcos shorty.ssl.berkeley.edu eagcos@shorty.ssl.berkeley.edu's password: (<i>get from SSL personnel</i>) Last login: Sat Oct 7 10:41:05 2000 from auntem.ssl.berke Sun Microsystems Inc. SunOS 5.8 Generic February 2000 You have mail. COS EGSE software version: devel	slogin as eagcos ; get password from SSL personnel

4.1.6 Set Current Directory

Step	QA	Operator Entry/System Response	Description
5		eagcos:shorty% cd /disks/galex/users/galex/tcs/uniscript/stp5_2_3_2 eagcos:shorty% pwd /disks/galex/users/galex/tcs/uniscript/stp5_2_3_2	Change current directory as shown

4.1.7 Ensure that Proper Files are Present

Step	QA	Operator Entry/System Response	Description
6		<pre>eagcos@shorty% ls -l Total 12 -rw-r--r-- 1 tcs eag 1398 Oct 8 18:03 stp5_2_3_2.tst -rw-r--r-- 1 tcs eag 62 Oct 9 17:44 u</pre>	List files; the .tst file and the shell script u should be present

4.2 OPERATION EXECUTION

4.2.1 Establish Initial Test Conditions

Step	QA	Operator Entry/System Response	Description
7		<pre>eagcos:shorty% set path=(\$path ~dbb/scripts/bin)</pre>	Set path as shown to enable access to hks tools

4.2.2 Execute the Script

Step	QA	Operator Entry/System Response	Description
8		<pre>eagcos:taiyo% more < u #!/bin/sh pkill cosnoopy perl ../UniScript.pl stp5_2_3_2 "0,0,0,0,0,0,0" cosnoopy& eagcos:taiyo% sh u \$psstring=0,0,0,0,0,0,0 Parameters are: Script File: stp5_2_3_2 #0: 0 #1: 0 #2: 0 #3: 0 #4: 0 #5: 0 #6: 0 #7: 0 Report file >/disks/galex/users/galex/tcs/uniscript/stp5_2_3_2/ stp5_2_3_2.rpl</pre>	Shell to u . You should see the accompanying output as UniScript executes

Step	QA	Operator Entry/System Response	Description
		successfully opened. Report file >/disks/galex/users/galex/tcs/uniscript/stp5_2_3_2/ stp5_2_3_2.rp2 successfully opened. Script file /disks/galex/users/galex/tcs/uniscript/stp5_2_3_2/st p5_2_3_2.tst successfully opened at level 0. "Sending POR" LFDNOOP WAIT 0: HKV0=1; HKV1=25; wc=5 "Transmitting synthesized LFDNOOP command with five non-zero parameters" "Waiting for HK data" WAIT 0: HKV0=2; HKV1=0; wc=1 WAIT 1: HKV1=2; wc=0 "Test stp 5.2.3.2 completed successfully"	

4.3 POST-OPERATION ACTIVITIES

4.3.1 Copy Reports to PC Files and Print Them

Using an FTP client, copy the **u**, **stp5_2_3_2.tst**, **stp5_2_3_2.rp1**, and **stp5_2_3_2.rp2** files to appropriate PC files. Include these files as Appendices A, B, C, and D with this completed form.

4.3.2 Complete The Test Procedure Form

Ensure that all blank fields in this report are completed correctly and submit the completed report to QA.

SUMMARY SHEET

OPERATION TITLE: _____ WOA# _____

TEST ARTICLES IDENTIFICATION (including serial and/or part numbers):

TASKS/STEPS COMPLETED: _____

LOCATION: _____

TEST STARTED:	TEST TERMINATED
TIME: _____ Hr/Min	TIME: _____ Hr/Min
DATE: _____	DATE: _____

LOGS USED: _____

ANOMALY REPORTS GENERATED: _____

COMMENTS: _____

TEST CONDUCTOR: _____
Signature/Date

QA REPRESENTATIVE: _____
Signature/Date

Appendix A. Shell Script u

```
#!/bin/sh  
kill cosnoopy  
perl ../UniScript.pl stp5_2_3_2 "0,0,0,0,0,0,0,0"  
cosnoopy&
```

Appendix B. Test Script stp5_2_3_2.tst

```
; *****  
; * STP 5.2.3.2 *  
; * ----- *  
; * Echoes for Command Opcodes and Parameters *  
; * ----- *  
; * Send a valid Command String with Serial Number and five parameters to the DCE. *  
; * Verify that the resulting HK packet contains the complete and proper Command *  
; * String echo. *  
; * ----- *  
; * NOTE that since no actual DCE command requires or permits 5 parameters, we use *  
; * a special command synthesized in Buffer 1, that is in fact a NOOP with para- *  
; * meters 0010, 0020, 0030, 0040, 0050. The S/N is 0001. *  
; *****  
;   
SYM DELTA=1  
ECHO 2  
;  
DTG 3,"(0) Sending POR"  
WTO "Sending POR"  
POR  
WAIT 1  
LFDNOOP  
WAIT 5,HK  
;  
; *****  
; * Synthesize goofy NOOP *  
; *****  
;  
DATA 1, 0,8,CONST=0x045AFFAF_04580050  
DATA 1, 8,8,CONST=0x0456FFBF_04540040  
DATA 1,16,8,CONST=0x0452FFCF_04500030  
DATA 1,24,8,CONST=0x044EFFDF_044C0020  
DATA 1,32,8,CONST=0x044AFFEF_04480010  
DATA 1,40,8,NEXT  
DATA 1,48,8,CONST=0x04427F7F_04408080  
;  
LOG 1,1  
;  
; *****  
; * Transmit the command to the DCE *  
; *****  
;  
DTG 3,"(1) Transmitting synthesized LFDNOOP command with five non-zero parameters"  
WTO "Transmitting synthesized LFDNOOP command with five non-zero parameters"  
XCMD 1  
;  
DTG 3,"(2) Waiting for HK data"  
WTO "Waiting for HK data"  
WAIT 5,HK  
LOG 1,LFDCCBUF,LFDIAGS  
;  
; *****  
; * Verify match *  
; *****  
;  
CHECK 1,($LFDCCBUF[ 0] == hex(substr($B1,108,4)))  
CHECK 1,($LFDCCBUF[ 1] == hex(substr($B1,100,4)))  
CHECK 1,($LFDCCBUF[ 2] == hex(substr($B1, 92,4)))  
CHECK 1,($LFDCCBUF[ 3] == hex(substr($B1, 84,4)))  
CHECK 1,($LFDCCBUF[ 4] == hex(substr($B1, 76,4)))  
CHECK 1,($LFDCCBUF[ 5] == hex(substr($B1, 68,4)))  
CHECK 1,($LFDCCBUF[ 6] == hex(substr($B1, 60,4)))  
CHECK 1,($LFDCCBUF[ 7] == hex(substr($B1, 52,4)))  
CHECK 1,($LFDCCBUF[ 8] == hex(substr($B1, 44,4)))  
CHECK 1,($LFDCCBUF[ 9] == hex(substr($B1, 36,4)))  
CHECK 1,($LFDCCBUF[10] == hex(substr($B1, 28,4)))  
CHECK 1,($LFDCCBUF[11] == hex(substr($B1, 20,4)))
```

Center for Astrophysics & Space Astronomy

```
CHECK 1, ($LFDCBUF[12] == hex(substr($B1, 12, 4)))  
CHECK 1, ($LFDCBUF[13] == hex(substr($B1, 4, 4)))  
;  
DTG 3, "(3) Test stp 5.2.3.2 completed successfully"  
WTO "Test stp 5.2.3.2 completed successfully"
```

Appendix C. Test Report stp5_2_3_2.rp1

```

222                55555                222                333
2                5                2 2                3 3                2
2                ssss ttttt pppp 555                2                3
2                s                t p p 5                2                3
2                sssss t pppp 5                2                3
2                s t p 5 5                2                3 3                2
22222            ssss t p 555 _____ 22222 _____ 333 _____

```

Ver 01.09 Fri Dec 1 00:31:40 2000 "(0) Sending POR"

LFDNOOP

```

Len  CRC  Buffer          Data
----  ----  -----  ----
0038 8E73 1          04 5A FF AF 04 58 00 50 04 56 FF BF 04 54 00 40 04 52 FF CF 04
50 00 30 04 4E FF DF 04 4C 00 20          04 4A FF EF 04 48 00 10 04 46 FF FD 04 44 00 02 04 42 7F 7F 04
40 80 80

```

Ver 01.09 Fri Dec 1 00:31:41 2000 "(1) Transmitting synthesized LFDNOOP command with five non-zero parameters"

Ver 01.09 Fri Dec 1 00:31:41 2000 "(2) Waiting for HK data"

```

Addr Addr HK-Name          Value
-----
1664-167F LFDPCBUF          8080 7F7F 0002 FFFD 0010 FFEF 0020 FFDF 0030 FFCF 0040
FFBF 0050 FFAF

1780-179F LFDIAGS           011B 0000 0000 0000 0000 0000 0000 0000 0000 0000 0000 0000
0000 0000 0000 0000 0000
17A0-17BF          0000 0000 0000 0000 0000 0000 0000 0000 0000 0000 0000
0000 0000 0000 0000

```

```

CHECK: ($LFDPCBUF[ 0] == hex(substr($B1,108,4)))
eval: (0000[ 0] == hex(substr(045A...,108,4)))

```

S U C C E S S

```

CHECK: ($LFDPCBUF[ 1] == hex(substr($B1,100,4)))
eval: (0000[ 1] == hex(substr(045A...,100,4)))

```

S U C C E S S

```

CHECK: ($LFDPCBUF[ 2] == hex(substr($B1, 92,4)))
eval: (0000[ 2] == hex(substr(045A..., 92,4)))

```

S U C C E S S

```

CHECK: ($LFDPCBUF[ 3] == hex(substr($B1, 84,4)))
eval: (0000[ 3] == hex(substr(045A..., 84,4)))

```

S U C C E S S

```

CHECK: ($LFDPCBUF[ 4] == hex(substr($B1, 76,4)))
eval: (0000[ 4] == hex(substr(045A..., 76,4)))

```

S U C C E S S

```

CHECK: ($LFDPCBUF[ 5] == hex(substr($B1, 68,4)))
eval: (0000[ 5] == hex(substr(045A..., 68,4)))

```

Center for Astrophysics & Space Astronomy

S U C C E S S

CHECK: (\$LFDCBUF[6] == hex(substr(\$B1, 60,4)))
eval: (0000[6] == hex(substr(045A..., 60,4)))

S U C C E S S

CHECK: (\$LFDCBUF[7] == hex(substr(\$B1, 52,4)))
eval: (0000[7] == hex(substr(045A..., 52,4)))

S U C C E S S

CHECK: (\$LFDCBUF[8] == hex(substr(\$B1, 44,4)))
eval: (0000[8] == hex(substr(045A..., 44,4)))

S U C C E S S

CHECK: (\$LFDCBUF[9] == hex(substr(\$B1, 36,4)))
eval: (0000[9] == hex(substr(045A..., 36,4)))

S U C C E S S

CHECK: (\$LFDCBUF[10] == hex(substr(\$B1, 28,4)))
eval: (0000[10] == hex(substr(045A..., 28,4)))

S U C C E S S

CHECK: (\$LFDCBUF[11] == hex(substr(\$B1, 20,4)))
eval: (0000[11] == hex(substr(045A..., 20,4)))

S U C C E S S

CHECK: (\$LFDCBUF[12] == hex(substr(\$B1, 12,4)))
eval: (0000[12] == hex(substr(045A..., 12,4)))

S U C C E S S

CHECK: (\$LFDCBUF[13] == hex(substr(\$B1, 4,4)))
eval: (0000[13] == hex(substr(045A..., 4,4)))

S U C C E S S

Ver 01.09 Fri Dec 1 00:31:42 2000 "(3) Test stp 5.2.3.2 completed successfully"

Appendix D. Test Report stp5_2_3_2.rp2

```

                55555          222          333
222                5          2  2          3  3          2
2                ssss ttttt pppp 555          2          3
2                s      t  p  p  5          2          3
2                sssss  t  pppp  5          2          3
2                s      t  p  5  5          2          3  3          2
                ssss  t  p  555  _____ 22222 _____ 333  _____
22222

```

Ver 01.09 Fri Dec 1 00:31:40 2000 "(0) Sending POR"

P O R P A C K E T

80000000

C O M M A N D P A C K E T

```

                PARM4          PARM3          PARM2          PARM1          PARM0
045AFFFF 04580000 0456FFFF 04540000 0452FFFF 04500000 044EFFFF 044C0000 044AFFFF 04480000
                SN          OPCODE
0446FFFE 04440001 04427F7F 04408080

```

Ver 01.09 Fri Dec 1 00:31:41 2000 "(1) Transmitting synthesized LFDNOOP command with five non-zero parameters"

C O M M A N D P A C K E T

```

                PARM4          PARM3          PARM2          PARM1          PARM0
045AFFAF 04580050 0456FFBF 04540040 0452FFCF 04500030 044EFFFDF 044C0020 044AFFEF 04480010
                SN          OPCODE
0446FFFD 04440002 04427F7F 04408080

```

Ver 01.09 Fri Dec 1 00:31:41 2000 "(2) Waiting for HK data"

C O M M A N D P A C K E T

```

                PARM4          PARM3          PARM2          PARM1          PARM0
045AFFFF 04580000 0456FFFF 04540000 0452FFFF 04500000 044EFFFF 044C0000 044AFFFF 04480000
                SN          OPCODE
0446FFFC 04440003 04427F7F 04408080

```

Ver 01.09 Fri Dec 1 00:31:42 2000 "(3) Test stp 5.2.3.2 completed successfully"